



Europäisches
Patentamt

European
Patent Office

Office européen
des brevets



Bescheinigung

Certificate

Attestation

Die angehefteten Unterlagen stimmen mit der ursprünglich eingereichten Fassung der auf dem nächsten Blatt bezeichneten europäischen Patentanmeldung überein.

The attached documents are exact copies of the European patent application described on the following page, as originally filed.

Les documents fixés à cette attestation sont conformes à la version initialement déposée de la demande de brevet européen spécifiée à la page suivante.

Patentanmeldung Nr. Patent application No. Demande de brevet n°

00307166.9

**CERTIFIED COPY OF
PRIORITY DOCUMENT**

Der Präsident des Europäischen Patentamts;
Im Auftrag

For the President of the European Patent Office

Le Président de l'Office européen des brevets
p.o.

I.L.C. HATTEN-HECKMAN

DEN HAAG, DEN
THE HAGUE, 22/03/01
LA HAYE, LE

This Page Blank (uspto)



Europäisches
Patentamt

European
Patent Office

Office européen
des brevets

**Blatt 2 der Bescheinigung
Sheet 2 of the certificate
Page 2 de l'attestation**

Anmeldung Nr.:
Application no.:
Demande n°: 00307166.9

Anmeldetag:
Date of filing: 21/08/00
Date de dépôt:

Anmelder:
Applicant(s):
Demandeur(s):
LUCENT TECHNOLOGIES INC.
Murray Hill, New Jersey 07974-0636
UNITED STATES OF AMERICA

Bezeichnung der Erfindung:
Title of the invention:
Titre de l'invention:
Transmission and reception device for base stations

In Anspruch genommene Priorität(en) / Priority(ies) claimed / Priorité(s) revendiquée(s)

Staat:
State:
Pays:

Tag:
Date:
Date:

Aktenzeichen:
File no.
Numéro de dépôt:

Internationale Patentklassifikation:
International Patent classification:
Classification internationale des brevets:
H04B1/04

Am Anmeldetag benannte Vertragsstaaten:
Contracting states designated at date of filing: AT/BE/CH/CY/DE/DK/ES/FI/FR/GB/GR/IE/IT/LI/LU/MC/NL/PT/SE
Etats contractants désignés lors du dépôt:

Bemerkungen:
Remarks:
Remarques:

See for original title page 1 of the description.

This Page Blank (uspto)

Lucent Technologies

00LUC0016EPP

Transmission and reception device for mobile radio

5 The invention relates to a transmission and reception device for a mobile radio base station comprising a plurality of transmission and reception units and hence a plurality of carriers, the transmission and reception units being accommodated in
10 push-in modules and each having a modulator, a channel frequency device and an output stage.

 A mobile radio base station usually serves a plurality of radio cells arranged sectorally with respect to the base station. Normally, three radio
15 cells are provided per base station. Each radio cell has a plurality of associated transmission and reception devices, for example four such units. The possibility of diversity reception means that one radio cell normally has two antennas which are also used for
20 transmission. In the example quoted, two transmission and reception units operate on one antenna. To enable this, so-called hybrid combiners are in use. When the carriers are combined, losses of 3 dB occur, which amounts to half the consumed power. A normal
25 transmitter output power is 40 W per transmission and reception unit. The losses are accordingly considerable and are converted to heat in a load resistor. The hybrid combiners themselves are accommodated in particular individual push-in units. Each antenna
30 additionally requires a duplex filter in order to separate the transmission and reception frequencies from one another.

 In the example quoted, there are thus twelve transmission and reception units at the base station,
35 which are accommodated in a so-called cabinet which is fully utilized.

 In practice, the growing interest in mobile radio has resulted in a further increase in the number

- 2 -

of carriers per cell. This can be achieved by means of a second fully stocked cabinet next to the first cabinet, so that the number of carriers is increased to twenty-four in the example given. For service
5 providers, this solution has the disadvantage that their rental costs are increased.

When a mobile network is set up, there are initially few cells and a small number of carriers, and it is therefore necessary to operate at high
10 transmitter output power in order to cover the relatively large cells. If the number of subscribers increases, then both the number of radio cells and the number of carriers per radio cell are increased. These radio cells are smaller and can be served at a lower
15 transmitter output power.

The invention is based on the object of designing a transmission and reception device of the type mentioned in the introduction such that operation can be matched to an increasing number of mobile radio
20 subscribers. In addition, the aim is to lower the outlay for installation and operation of the transmission and reception device.

The object which is set is achieved on the basis of the features of the main claim and is refined
25 and developed further by the further features of the dependent claims.

The following advantages can be achieved with the invention's design of the transmission and reception device:
30 the mobile radio network can be developed in stages. At the start of network development, a high output power is available, while, as the number of subscribers increases, a two-carrier mode can be used to change over to a higher capacity.

35 To adapt to particular radio conditions, it is also possible to change over between a high-power mode and a high-capacity mode during continuous operation. In this case, use is made of the circumstance that the transmitters connected to one another by means of the

- 3 -

hybrid combiner are operated in time slots which are synchronized with one another. The changeover from high power to high capacity is carried out on the basis of time slots.

5 If the hybrid combiner is also incorporated in the push-in module in addition to the first and second transmission and reception units, less outlay is required for the cables, and two radiofrequency cables per transmission and reception unit are dispensed with.
10 This elimination also results in the power loss being reduced. Further cost reductions result from the elimination of the otherwise necessary extra housing for the hybrid combiner. The solution according to the invention also enables the costs of isolation in the
15 output stage to be reduced.

The invention is described with the aid of the drawing, in which:

Figure 1 shows a first embodiment of the transmission
part of the transmission and reception unit,
20 and
Figure 2 shows a second embodiment of the transmission part of the transmission and reception unit.

The block circuit shown in Figure 1 comprises a transmission branch 1, a transmission branch 2 and a
25 hybrid combiner 3 with a transmitter output 4. Each transmission branch 1, 2 comprises a modulator 10 and a first oscillator 11 which are connected to a mixer 12 and to a first bandpass filter 13 in order to supply a modulated frequency signal to an amplifier 14. Second
30 oscillators 15 are in the form of toggle synthesizers and are connected to a second mixer 16, to which the output of the amplifier 14 is also connected. The power of the resultant frequency signal is regulated in a power amplifier 17 and is supplied to a second bandpass
35 filter 18. Parts 11 to 18 form a channel frequency device 19. This is adjoined by an output stage 20 which contains a power amplifier 21, an isolator 22 and possibly a phase shifter 23. In addition, the output stage 20 has an associated power detector 24. The two

- 4 -

transmission branches 1 and 2 are also connected to one another via a combination switch 25 which enables the output of the channel frequency device 19 in the second transmission branch 2 to be connected to the input of the output stage 20 in the first transmission branch 1.

The dual transmission and reception unit shown has only one transmission connection 4, which is located on the hybrid combiner 3. The transmission branches 1 and 2 are operated such that 2×20 W are available in combination at the transmission connection 4. It should be noted that combination losses arise at the same level.

To achieve in-phase operation for the two output stages 20, the signal transit times of the two output stages and of the isolators need either to be matched very precisely or to be tuned.

The hybrid combiner 3 is used to add the two signals from the transmission branches 1 and 2 and to output them at the transmission connection 4. If the hybrid combiner 3 used is a so-called branch arm coupler comprising stripline structures, an additional $\lambda/4$ line is used as the phase shifting device 23 in order to bring about a 90° phase shift in one of the branches 1 or 2 (shown in branch 1 in this case). The branch arm coupler then provides in-phase addition of the signals from the two transmission branches 1 and 2.

The phase shifting device 23 need not be arranged directly at the input of the hybrid combiner 3; it may also be arranged directly upstream of the power amplifier 21. Such an arrangement has the advantage that the signal power upstream of the power amplifier 21 is low, and hence the power loss is also still low.

If the combination switch 25 in Figure 1 is thrown, then the channel frequency device 19 in the transmission branch 2 operates on the output stages 20 of both transmission branches 1 and 2, i.e. the two transmitter output stages 20 are operated at the same frequency and using the same data. In such a case, the

- 5 -

hybrid combiner 3 can be driven such that the losses of 3 dB which arise otherwise do not arise when the carriers are combined, i.e. the two input signals, coming from the transmission branches, at the combiner are added if the phases coincide. If the two transmission branches are each designed for 40 watts, then 80 watts are available at the transmitter output 4. The invention is therefore particularly suitable for the initial structure of the mobile radio network, where the individual radio cells still have a large surface area.

Figure 2 shows a further illustrative embodiment of the invention in the form of a block diagram. Where there is correspondence with the first illustrative embodiment, the same reference numerals are used and reference is made to the pertaining description. The operation using combined carriers at the output 4 is the same as in the first illustrative embodiment. The embodiment shown in Figure 2 likewise allows a high output power to be output at the transmitter output 4. In this regard, the transmission branches 1 and 2 are operated using the same data, frequencies and phases. The following measures are taken in this regard:

the modulators used are, by way of example, DSP (Digital Signal Processor) devices with downstream D/A converters, so that the two branches can be operated using the same data. The frequency and phase coincidence of the two transmission branches 1 and 2 is produced by using the oscillators of only one branch, in this case the transmission branch 1. A first changeover switch 26 is provided in order to apply the signal from the oscillator 11 in the transmission branch 1 to the mixer 12 in the transmission branch 2, and a further changeover switch 27 is provided in order to connect the oscillator 15 in the transmission branch 1 to the mixer 16 in the transmission branch 2. If small phase shifts arise, this can be compensated for at the modulators 10. Amplitude differences can be

- 6 -

compensated for by tuning the modulators or by making appropriate adjustments on the amplifiers 17. The losses in the hybrid combiner 3 and in the isolators 20 and possibly the phase shifting unit 23 have been
5 determined previously; the actual output power can therefore be ascertained on the basis of the power measured using the power detectors 24.

- 7 -

Patent Claims

1. Transmission and reception device for a mobile radio base station comprising a plurality of transmission and reception units and hence a plurality of carriers, the transmission and reception units being accommodated in push-in modules and each having a modulator (10), a channel frequency device (19) and an output stage (20),
- 5 characterized by the following features:
- at least some of the push-in modules comprise two full transmission and reception units having a first and a second transmission branch (1, 2);
- the two transmission branches (1, 2) are
- 15 connected to a transmission connection (4) via an incorporated hybrid combiner (3) in order to provide two mutually combined carriers in a first mode of operation for relatively high capacity;
- in a second mode of operation for high output
- 20 power, the two transmission branches (1, 2) are additionally connected to one another by means of an internal changeover device (25, 26, 27) such that the same transmitted signal is routed at least via the output stages (20) of both transmission branches (1,
- 25 2).
2. Transmission and reception device according to Claim 1, characterized in that the internal changeover device comprises a combination switch (25) which connects the output of the channel frequency device
- 30 (19) in one transmission branch (2) to both output stages (20).
3. Transmission and reception device according to Claim 2, characterized in that the same transit time delay can be set for both output stages (20).
- 35 4. Transmission and reception device according to one of Claims 1 to 3, characterized in that the hybrid combiner (3) is in the form of a branch arm coupler and in that a 90° phase shifting device (23) is provided in

- 8 -

the course of the output stage (20) of one transmission branch (1).

5. Transmission and reception device according to Claim 4, characterized in that the 90° phase shifting device (23) is connected directly upstream of the hybrid combiner (3).



6. Transmission and reception device according to Claim 4, characterized in that the 90° phase shifting device (23) is connected directly upstream of the amplifier (21) in the output stage (20).

7. Transmission and reception device according to one of Claims 1 to 6, characterized in that the internal changeover devices (26, 27) cover the connection of frequency-generating elements (11, 15) in one branch (1) to mixers (12, 16) in the other branch (2).

Abstract

Transmission and reception device for a mobile radio base station comprising a plurality of transmission and reception units and hence a plurality of carriers, the transmission and reception units being accommodated in push-in modules and each having a modulator (10), a channel frequency device (19) and an output stage (20). At least some of the push-in modules comprise two full transmission and reception units having a first and a second transmission branch (1, 2). The two transmission branches (1, 2) are connected to a transmission connection (4) via an incorporated hybrid combiner (3) in order to provide two mutually combined carriers in a first mode of operation for relatively high capacity. In a second mode of operation for high output power, the two transmission branches (1, 2) are additionally connected to one another by means of an internal changeover device (25, 26, 27) such that the same transmitted signal is routed at least via the output stages (20) of both transmission branches (1, 2).

This Page Blank (uspto)



This Page Blank (uspto)